TX-SR343 5.1-Channel A/V Receiver

BLACK

ONKYO





Surround Sound for Immersive 4K Entertainment

Behind the freshly styled faceplate of the TX-SR343 is high-current Wide Range Amplification Technology to transform your movie, television, and gaming experiences. This receiver has the latest HDMI® 2.0a connections and supports HDCP 2.2, which means you can stream UltraHD video and spin next-generation 4K Blu-rays. The TX-SR343 is also ready to power and play USB video-subscription streaming devices. The TX-SR343 can up-convert analog video (such as VHS tapes) and send it to your TV through a single HDMI cable for improved picture quality. There's Bluetooth streaming with audio optimization, and a Burr-Brown DAC to ensure your music is played with pure energy. It's quite simply our best budget A/V receiver ever.

HIGHLIGHTS

- 110 W per Channel
- HDMI 4 In / 1 Out (4K UltraHD / HDMI / HDCP 2.2)
- True Driving Power from Discrete Amp Circuits
- Bluetooth Audio Streaming
- Easy Configuration Rear Panel
- HDMI Video Up-Conversion
- Streaming Media Player Ready

ADVANCED FEATURES

- 4K/60 Hz-Capable HDMI® Terminals for UltraHD Entertainment
- Bluetooth Version 2.1 + EDR Capability (Compatible Profile: A2DP vI.2, AVRCP vI.3)
- Analog Video Upconversion to HDMI
- Advanced Music Optimizer to Improve Compressed Digital
- Audio Quality (Bluetooth Audio Included)
- Phase-Matching Bass Boost for Deep Bass and Clear Mid-Range

AMPLIFIER FEATURES

- I 10 W/Ch (6 Ohms, I kHz, 0.9% THD, I Channel Driven, FTC);
 65 W/Ch (8 Ohms, 20 Hz–20 kHz, 0.7% THD, 2 Channels Driven, FTC)
- WRAT (Wide Range Amplifier Technology)
- H.C.P.S. (High Current Power Supply) Massive High Power Transforme
- Discrete Output Stage Circuitry
- PLL (Phase Locked Loop) Jitter-Cleaning Circuit Technology for S/PDIF Audio

PROCESSING FEATURES

- HDMI® Support for 4K/60 Hz, 3D,Audio Return Channel, DeepColor[™], x.v.Color[™], LipSync, Dolby® TrueHD, DTS-HD Master Audio[™], DVD-Audio, Super Audio CD, Multichannel PCM, and CEC
- Dolby® TrueHD and DTS-HD Master Audio[™] Decoding • TI Burr-Brown 192 kHz/24-bit DAC for All Channels
- Advanced 32-bit DSP Chip
- 4 DSP Modes for Gaming: Rock, Sports, Action, and RPG
- Theater-Dimensional Virtual Surround Function
- CinemaEll TER
- Direct Mode
- Double Bass Function
- Non-Scaling Configuration
- A-Form Listening Mode Memory

CONNECTION FEATURES

- 4 HDMI Inputs and I Output
- USB Port (Rear) for Powering Media Streaming Sticks (5 V, I A)
- 2 Component Video Inputs (Rear)
- 3 Composite Video Inputs (I Front/2 Rear)
- 3 Digital Audio Inputs (2 Optical and I Coaxial)
- 7 Analog Audio Inputs (I Front/6 Rear)
- Subwoofer Pre-Out
- Headphone Jack

OTHER FEATURES

- Crossover Adjustment for Each Channel
- (40/50/60/70/80/90/100/120/150/200 Hz)
- A/V Sync Control (Up to 500 ms in 10 ms Steps at 48 kHz) • Overlaid On-Screen Display (OSD) via HDMI with Quick
- Set-Up HDMI® Passthrough Function
- Tone Control (Bass/Treble) for Front L/R Channels
- 3-Mode Display Dimmer (Normal/Dim/Dimmer)
- 40 FM/AM Random Presets
- RIHD (Remote Interactive Over HDMI) for System Control
- Full-Function RI (Remote Interactive) Remote Control

TX-SR343 5.1-Channel A/V Receiver

HDMI[®] 4 In / I Out for UltraHD

All HDMI terminals support the latest TV 4K/60 Hz video displays, and comply with HDCP 2.2 copy protection encoded in content from movie studios, broadcasters, and streaming services, for next-generation UltraHD.



True Power from Discrete Amplifiers

Discrete Amps deliver high instantaneous current to increase speaker control for accurate and dynamic audio reproduction. This precise power is the cornerstone of Onkyo's amplification philosophy.



Easy Connection Guide on Back Panel

Connections to speakers and external devices are illustrated and clearly labeled on the back panel.




Bluetooth Audio Streaming

Stream virtually any audio from your smartphone, tablet, or PC to your home theater for clear and powerful sound.



HDMI Video Up-Conversion

Only one wire! Every video signal is converted and sent to your TV through one HDMI cable.



Ready for Streaming Media Devices

The handy USB port supplies power to streaming media players. Keep up with your video subscription services and other programs streamed from the Internet.



(Streaming device not included)

SPECIFICATIONS

	1
Power Output	
Front L/R	110 W/Ch (6 Ohms, 1 kHz, 0.9% THD,
	I Channel Driven, FTC) 65 W/Ch (8 Ohms, 20 Hz–20 kHz,
	0.7% THD, 2 Channels Driven, FTC)
Center	110 W (6 Ohms, 1 kHz, 0.9% THD,
center	I Channel Driven, FTC)
	65 W (8 Ohms, 20 Hz–20 kHz, 0.7% THD,
	2 Channels Driven, FTC)
Surround L/R	110 W/Ch (6 Ohms, 1 kHz, 0.9% THD,
	I Channel Driven, FTC)
	65 W/Ch (8 Ohms, 20 Hz–20 kHz,
	0.7% THD, 2 Channels Driven, FTC)
Dynamic Power	160 W (3 Ohms, Front)
	125 W (4 Ohms, Front)
	85 W (8 Ohms, Front)
THD+N (Total Harmon	
	0.08% (20 Hz–20 kHz, Half Power)
Damping Factor	Over 40 (Front, I kHz, 8 Ohms)
Input Sensitivity and Imp	
input sensitivity and imp	
Pated BCA Othersty	200 mV/47 k-ohms (Line)
Rated RCA Output Leve	er and impedance
	I V/470 Ohms (Subwoofer Pre Out)
Frequency Response	10 Hz–100 kHz/+1 dB, -3 dB (Direct Mode
Tone Control	±10 dB, 20 Hz (Bass)
	±10 dB, 20 kHz (Treble)
Signal-to-Noise Ratio	100 dB (Line, IHF-A)
Speaker Impedance	6 Ohms–16 Ohms
Video Section	
Input Sensitivity/Output	
Video	1.0 Vp–p/75 Ohms (Component Y)
	0.7Vp-p/75 Ohms (Component PB/CB, PR/CF
	0.7Vp-p/75 Ohms (Component PB/CB, PR/CF 1.0Vp-p/75 Ohms (Composite)
Component Video Frequ	0.7Vp–p/75 Ohms (Component PB/CB, PR/Ci 1.0Vp–p/75 Ohms (Composite) uency Response
	0.7Vp-p/75 Ohms (Component PB/CB, PR/Ci 1.0Vp-p/75 Ohms (Composite)
	0.7Vp–p/75 Ohms (Component PB/CB, PR/Ci 1.0Vp–p/75 Ohms (Composite) uency Response
	0.7Vp-p/75 Ohms (Component PB/CB, PR/CI 1.0Vp-p/75 Ohms (Composite) uency Response 5 Hz-13.5 MHz/+0 dB,-3 dB
Tuner Section	0.7Vp-p/75 Ohms (Component PB/CB, PR/CI 1.0Vp-p/75 Ohms (Composite) uency Response 5 Hz-13.5 MHz/+0 dB,-3 dB
Tuner Section Tuning Frequency Range	0.7Vy-p/75 Ohms (Component PB/GB, PR/G 1.0Vp-p/75 Ohms (Composite) uency Response 5 Hz-13.5 MHz/+0 dB, -3 dB 8.5 MHz-107.9 MHz
Tuner Section Tuning Frequency Range FM AM	0.7Vp-pr/5 Ohms (Component PB/CB, PR/CI 1.0Vp-pr/5 Ohms (Composite) uency Response 5 Hz-13.5 MHz/+0 dB, -3 dB 87.5 MHz-107.9 MHz 530 kHz-1.710 kHz
Tuner Section Tuning Frequency Range FM AM FM/AM Preset Memory	0.7Vp-pr/5 Ohms (Component PB/CB, PR/CI 1.0Vp-pr/5 Ohms (Composite) uency Response 5 Hz-13.5 MHz/+0 dB, -3 dB 87.5 MHz-107.9 MHz 530 kHz-1,710 kHz
Tuner Section Tuning Frequency Range FM AM FM/AM Preset Memory General	0.7Vp-pr/5 Ohms (Component Pa/CB, PR/CI 1.0Vp-pr/5 Ohms (Composite) uency Response 5 Hz-13.5 MHz/+0 dB, -3 dB 87.5 MHz-107.9 MHz 530 kHz-1.710 kHz 40 Stations
Tuner Section Tuning Frequency Range FM AM FM/AM Preset Memory General Power Supply	0.7Vp-pr/5 Ohms (Component Pa/CB, PR/CJ 1.0Vp-pr/5 Ohms (Composite) uency Response 5 Hz-13.5 MHz/+0 dB, -3 dB 87.5 MHz-107.9 MHz 530 kHz-1,710 kHz 40 Stations AC 120V~, 60 Hz
Tuner Section Tuning Frequency Range FM AM FM/AM Preset Memory	0.7Vp-pr/5 Ohms (Component Pa/CB, PR/CJ 1.0Vp-pr/5 Ohms (Composite) uency Response 5 Hz-13.5 MHz/+0 dB, -3 dB 87.5 MHz-107.9 MHz 530 kHz-1,710 kHz 40 Stations AC 120V~, 60 Hz
Tuner Section Tuning Frequency Range FM AM FM/AM Preset Memory General Power Supply Power Consumption	0.7Vp-pr/5 Ohms (Component Pa/CB, Pk/CI 1.0Vp-pr/5 Ohms (Composite) uency Response 5 Hz-13.5 MHz/+0 dB, -3 dB 87.5 MHz-107.9 MHz 530 kHz-1,710 kHz 40 Stations AC 120V~, 60 Hz 3.8 A
Tuner Section Tuning Frequency Range FM AM FM/AM Preset Memory General Power Supply Power Consumption No-Sound Power Consu	0.7Vp-pr/5 Ohms (Component Pa/CB, Pk/CI 1.0Vp-pr/5 Ohms (Composite) uency Response 5 Hz-13.5 MHz/+0 dB, -3 dB 8 8.7.5 MHz-107.9 MHz 530 kHz-1,710 kHz 40 Stations AC 120V-, 60 Hz 3.8 A umption From From From From From From From From
Tuner Section Tuning Frequency Range FM AM FM/AM Preset Memory General Power Supply Power Consumption No-Sound Power Consu	0.7Vp-pr/5 Ohms (Component Pa/CB, Pk/CI 1.0Vp-pr/5 Ohms (Composite) uency Response 5 Hz-13.5 MHz/+0 dB, -3 dB 8.7.5 MHz-107.9 MHz 530 kHz-1,710 kHz 40 Stations AC 120V-, 60 Hz 3.8 A umption 50 W
Tuner Section Tuning Frequency Range FM AM FM/AM Preset Memory General Power Supply Power Consumption No-Sound Power Consum Standby Power Consum	0.7Vp-pr/5 Ohms (Component Pa/CB, Pk/CI 1.0Vp-pr/5 Ohms (Composite) uency Response 5 Hz-13.5 MHz/+0 dB, -3 dB 87.5 MHz-107.9 MHz 530 kHz-1.710 kHz 40 Stations AC 120V-, 60 Hz 3.8 A umption 50 W 0.15 W
Tuner Section Tuning Frequency Range FM AM Freset Memory General Power Supply Power Consumption No-Sound Power Consum Standby Power Consum	0.7Vp-pr/5 Ohms (Component Pa/CB, Pk/CI 1.0Vp-pr/5 Ohms (Composite) uency Response 5 Hz-13.5 MHz/+0 dB, -3 dB 87.5 MHz-107.9 MHz 530 kHz-1.710 kHz 40 Stations AC 120V-, 60 Hz 3.8 A umption 50 W 0.15 W
Tuner Section Tuning Frequency Range FM AM FM/AM Preset Memory General Power Supply Power Consumption No-Sound Power Consum Standby Power Consum	0.7Vp-pr/5 Ohms (Component Pa/CB, PR/CJ 1.0Vp-pr/5 Ohms (Composite) uency Response 5 Hz-13.5 MHz/+0 dB, -3 dB 87.5 MHz-107.9 MHz 530 kHz-1,710 kHz 40 Stations AC 120V~, 60 Hz 3.8 A umption 50 W ption 0.15 W 17 V ₆ × 6 ⁵ /t ₆ × 12 ¹⁵ /t ₆ *
Tuner Section Tuning Frequency Range FM FM FM/AM Preset Memory General Power Supply Power Consumption No-Sound Power Consum Standby Power Consum Dimensions (W × H × E	0.7Vp-pr/5 Ohms (Component Pa/CB, Pk/CF 1.0Vp-pr/5 Ohms (Composite) uency Response 5 Hz-13.5 MHz/+0 dB, -3 dB 87.5 MHz-107.9 MHz 530 kHz-1,710 kHz 40 Stations AC 120V-, 60 Hz 3.8 A umption 50 W ption 0.15 W 0) 17 1/z × 6 ⁵ / ₁₆ × 12 ⁻¹⁵ / ₁₆ ² (435 × 160 × 328 mm)
Tuner Section Tuning Frequency Range FM FM FM/AM Preset Memory General Power Supply Power Consumption No-Sound Power Consum Standby Power Consum Dimensions (W × H × E	0.7Vp-pr/5 Ohms (Component Pa/CB, PR/CF 1.0Vp-pr/5 Ohms (Composite) uency Response 5 Hz-13.5 MHz/+0 dB, -3 dB 87.5 MHz-107.9 MHz 530 kHz-1,710 kHz 40 Stations AC 120V~, 60 Hz 3.8 A umption 50 W ption 0.15 W 17 V ₆ × 6 5/t ₆ × 12 ¹⁵ /t ₆ "
Tuner Section Tuning Frequency Range FM AM FM/AM Preset Memory General Power Consumption No-Sound Power Consum Standby Power Consum Dimensions (W x H x E Weight	0.7Vp-pr/5 Ohms (Component Pa/CB, Pk/CF 1.0Vp-pr/5 Ohms (Composite) uency Response 5 Hz-13.5 MHz/+0 dB, -3 dB 87.5 MHz-107.9 MHz 530 kHz-1,710 kHz 40 Stations AC 120V-, 60 Hz 3.8 A umption 50 W ption 0.15 W 0) 17 1/z × 6 ⁵ / ₁₆ × 12 ⁻¹⁵ / ₁₆ ² (435 × 160 × 328 mm)
Tuner Section Tuning Frequency Range FM AM FM/AM Preset Memory General Power Supply Power Consumption No-Sound Power Consum Standby Power Consum Dimensions (W x H x E Weight CARTON	0.7Vp-pr/5 Ohms (Component Pa/CB, Pk/CF 1.0Vp-pr/5 Ohms (Composite) uency Response 5 Hz-13.5 MHz/+0 dB, -3 dB 87.5 MHz-107.9 MHz 530 kHz-1,710 kHz 40 Stations AC 120V-, 60 Hz 3.8 A umption 50 W ption 0.15 W ption 0.15 W 0.15 W 0.1
Tuner Section Tuning Frequency Range FM AM FM/AM Preset Memory General Power Supply Power Consumption No-Sound Power Consum Standby Power Consum Dimensions (W x H x E Weight CARTON	0.7Vp-pr75 Ohms (Component Pa/CB, Pk/CF 1.0Vp-pr/75 Ohms (Composite) uency Response 5 Hz-13.5 MHz/+0 dB, -3 dB 87.5 MHz-107.9 MHz 530 kHz-1.710 kHz 40 Stations AC 120V-, 60 Hz 3.8 A umption 50 W ption 0.15 W 0.15 W 1.7 / k^ x 6 % x 12 % x 1
Tuner Section Tuning Frequency Range FM AM FM/AM Preset Memory General Power Supply Power Consumption No-Sound Power Consum Standby Power Consum Dimensions (W × H × E Weight CARTON Dimensions (W × H × E	0.70/v-pr75 Ohms (Component Pa/CB, Pk/CF 1.0Vp-pr/5 Ohms (Composite) uency Response 5 Hz-13.5 MHz/+0 dB, -3 dB 87.5 MHz-107.9 MHz 500 kHz-1.710 kHz 40 Stations AC 120V-, 60 Hz 38.A umption 50 W 50 W
Tuner Section Tuning Frequency Range FM AM FM/AM Preset Memory General Power Supply Power Consumption No-Sound Power Consum Standby Power Consum Dimensions (W × H × E Weight CARTON Dimensions (W × H × E	0.7Vp-pr75 Ohms (Component Pa/CB, Pk/CF 1.0Vp-pr/75 Ohms (Composite) uency Response 5 Hz-13.5 MHz/+0 dB, -3 dB 87.5 MHz-107.9 MHz 530 kHz-1.710 kHz 40 Stations AC 120V-, 60 Hz 3.8 A umption 50 W ption 0.15 W 0.15 W 1.7 / k^ x 6 % x 12 % x 1
Tuner Section Tuning Frequency Range FM AM BYDAM Preset Memory General Power Supply Power Consumption No-Sound Power Consum Standby Power Consum Dimensions (W × H × E Weight CARTON Dimensions (W × H × E Weight	0.70/v-pr75 Ohms (Component Pa/CB, Pk/CF 1.0Vp-pr/5 Ohms (Composite) uency Response 5 Hz-13.5 MHz/+0 dB, -3 dB 87.5 MHz-107.9 MHz 500 kHz-1.710 kHz 40 Stations AC 120V-, 60 Hz 38.A umption 50 W 50 W
Tuner Section Tuning Frequency Range FM AM FM/AM Preset Memory General Power Supply Power Consumption No-Sound Power Consum Dimensions (W x H x D Weight CARTON Dimensions (W x H x D Weight UPC CODE	0.70/v-pr75 Ohms (Component Pa/CB, Pk/CF 1.0Vp-pr/5 Ohms (Composite) uency Response 5 Hz-13.5 MHz/+0 dB, -3 dB 87.5 MHz-107.9 MHz 500 kHz-1.710 kHz 40 Stations AC 120V-, 60 Hz 38.A umption 50 W 50 W
Tuner Section Tuning Frequency Range FM AM FM/AM Preset Memory General Power Supply Power Consumption No-Sound Power Consum Dimensions (W x H x D Weight CARTON Dimensions (W x H x D Weight UPC CODE	0.70/v-pr75 Ohms (Component Pa/CB, Pk/CF 1.0Vp-pr/5 Ohms (Composite) uency Response 5 Hz-13.5 MHz/+0 dB, -3 dB 87.5 MHz-107.9 MHz 500 kHz-1.710 kHz 40 Stations AC 120V-, 60 Hz 38.A umption 50 W 50 W
Tuner Section Tuning Frequency Range FM AM BYDAM Preset Memory General Power Supply Power Consumption No-Sound Power Consum Standby Power Consum Dimensions (W × H × E Weight CARTON Dimensions (W × H × E Weight	0.70 p-p/75 Ohms (Component Pa/CB, PA/CE 1.01 p-p/75 Ohms (Composite) uency Response 5 Hz-13.5 MHz/+0 dB, -3 dB 87.5 MHz-107.9 MHz 530 kHz-1.710 kHz 40 Stations AC 120V-, 60 Hz 3.8 A umption 50 W 50

Indoor FM antenna • AM loop antenna • Instruction manual
 Remote controller • AA (R6) batteries × 2



Text on receiver may vary with region.

Due to a policy of continuous product improvement, Onkyo reserves the right to change specifications and appearance without notice. Manufactured under license from Dolby Laboratories. Dolby and the double-D symbol are trademarks of Dolby Laboratories. For DTS patents, see http://jatents.dts.com.Manufactured under license from DTS. Licensing Limited, DTS, DTS-HD, the Symbol, & DTS and the Symbol together are registered trademarks, and DTS-HD Matter Audio is a trademark of DTS, Inc. M Rights Reserved. HDMI, the HDMI logo, and High. Definition Myliterined Interface are trademarks of DDIs Corporation. All other trademarks of HDMI. Licensing License the United States and other countries. The Bluetooth® word mark and logos are owned by the Bluetooth SIG, Inc. WRAT, Music Optimizer, GnemaRILTER, and Theater-Dimensional are trademarks of Onkyo Corporation. All other trademarks and registered trademarks are the property of their respective holders.



Copyright © 2015 Onkyo Corporation.All rights reserved.